

SMART PAC III™

FREE Warranty Upgrade
with Installation*

hes
ASSA ABLOY

- In-line power controller
- Continuous duty; reduces initial voltage by 25% after a fixed period of time
- Provides cooler, more efficient operation of strike
- Accepts wide range of input voltage: 12-32 Volts AC or DC
- Built-in surge protection
- Output 12VDC or 24VDC, depending on input voltage
- Supports fail secure or fail safe configured electric strikes
- Self-resetting fuse protects strike against over-current condition
- Can be used with all HES or Folger Adam electric strikes
- Can be used with Adams Rite electric strikes and electrified locks
- Diagnostics for voltage detection



LED Status Indicator Table

	LED COLOR	INPUT CONDITION	OUTPUT CONDITION	CORRECTIVE ACTION
1	Steady Green	10.5-21V*	15 VDC MAX STEPPING TO 9 VDC	NONE REQUIRED
2	Steady Yellow	21-33V*	30 VDC MAX STEPPING TO 18 VDC	NONE REQUIRED
3	Off or Blinking Green	TOO LOW (min. 10.5V)	~0	INCREASE VOLTAGE
4	Blinking Yellow	TOO HIGH (>33V)	~0	DECREASE VOLTAGE
5	Blinking 2 Yellow/2 Green	ANY	WRONG SLIDE SWITCH POSITION	CHANGE SLIDE SWITCH POSITION
6	Blinking Yellow/Green	ANY	DOWNSTREAM SHORT	FIND AND REMOVE SHORT

*See input requirements in installation instructions

*Installing a SMART Pac III™ power controller with any new product extends the 1 year warranty on electrical components, including the SMART Pac III™, to the full 3-5 year warranty term applicable to each Series mechanical components as outlined in HES' Standard Terms and Conditions.